

## VIC 20 Screen Memory

To move the screen: POKE 36869, (PEEK(36869) AND 15) OR X  
POKE 36866, (PEEK(36866) AND 127) OR Y

X	Y	4*(PEEK(36866) AND 128) + 64*(PEEK(36869) AND 112) = Location	
		Decimal (1/2K blocks)	Hexadecimal
128	0	0	\$0000
128	128	512	\$0200
129	0	1024	0400
129	128	1536	0600
130	0	2048	0800
130	128	2560	0A00
131	0	3072	0C00
131	128	3584	0E00
132	0	4096	1000 (dflt w/exp)
132	128	4608	1200
133	0	5120	1400
133	128	5632	1600
134	0	6144	1800
134	128	6656	1A00
135	0	7168	1C00
135	128	7680	1E00 (default)
136	0	8192	2000
136	128	8704	2200
137	0	9216	2400
137	128	9728	2600
138	0	10240	2800
138	128	10752	2A00
139	0	11264	2C00
139	128	11776	2E00
140	0	12288	3000
140	128	12800	3200
141	0	13312	3400
141	128	13824	3600
142	0	14336	3800
142	128	14848	3A00
143	0	15360	3C00
143	128	15872	3E00

## Commodore 64 Screen Memory

To move the screen: POKE 53272, (PEEK(53272)AND15) OR X

X	(3-PEEK(56576) AND 3) * 16384 + (X*64) = Location For Screen at Bank 0 (default):	
	Decimal	Hexadecimal
0	0	\$0000
16	1024	0400 (default)
32	2048	0800
48	3072	0C00
64	4096	1000
80	5120	1400
96	6144	1800
112	7168	1C00
128	8192	2000
144	9216	2400
160	10240	2800
176	11264	2C00
192	12288	3000
208	13312	3400
224	14336	3800
240	15360	3C00

## Commodore 64 VIC II Address

To move VIC II: POKE 53272, (PEEK(53272) AND 252) OR X ; X = 3-Bank#

Bank	X	VIC II Chip Address Range	
		Decimal (16K blocks)	Hexadecimal
0	3	0-16383	\$0000-3FFF (default)
1	2	16384-32767	4000-7FFF
2	1	32768-49151	8000-BFFF
3	0	49152-65535	C000-FFFF

Note: Character ROM only available with VIC II in bank 0 or 2

## VIC 20 Character Base

To move the character base: POKE 36869, (PEEK(36869) AND 240) OR X

X*	32768 + (PEEK(36869) AND 15) * 1024 = Location	
	Decimal (1K blocks)	Hexadecimal
0	32768-34815	\$8000-87FF (dflt)
1	33792-35839	8400-8BFF
2	34816-36863	8800-8FFF
3	35840-37887	8C00-93FF
4	36864-38911	9000-97FF
5	37888-39935	9400-9BFF
6	38912-40959	9800-9FFF
7	39936-41983	9C00-A3FF
8	0-2047	0000-07FF
9	1024-3071	0400-0BFF
10	2048-4095	0800-0FFF
11	3072-5019	0C00-13FF
12	4096-6143	1000-17FF
13	5020-7167	1400-1BFF
14	6144-8191	1800-1FFF
15	7168-9216	1C00-23FF

\* X = PEEK(36869) AND 15

## Commodore 64 Character Base

To move the character base: POKE 53272, (PEEK(53272) AND 240) OR X

X*	(3-PEEK(56576) AND 3) * 16384 + (X*64) = Location For Screen at Bank 0 (default):	
	Decimal (2K blocks)	Hexadecimal
0	0-2047	\$0000-07FF
2	2048-4095	0800-0FFF
4	4096-6143	1000-17FF *1
6	6144-8191	1800-1FFF *2
8	8192-10293	2000-27FF
10	10240-12287	2800-2FFF
12	12288-14335	3000-37FF
14	14336-16383	3800-3FFF

\* - X = PEEK(53272) AND 14

\*1 - Lower 2K of Character ROM (Bank 0 or 2 only) (default)

\*2 - Upper 2K of Character ROM (Bank 0 or 2 only)

## Character ROM Contents

Character ROM is the same in all machines, but only addressable in VIC 20/C64

2K Block	VIC 20		Commodore 64			Contents
	Default Address		Default Address		VIC II Image	
	Dec (1/2K blocks)	Hex	Dec (1/2K blocks)	Hex	Hex	
0	32768-33279	8000-81FF	53248-53759	D000-D1FF	1000-11FF	Upper case characters
	33280-33791	8200-83FF	53760-54271	D200-D3FF	1200-13FF	Graphics characters
1	33792-34303	8400-85FF	54272-54783	D400-D5FF	1400-15FF	Reversed upper case characters
	34304-34815	8600-87FF	54784-55295	D600-D7FF	1600-17FF	Reversed graphics characters
	34816-35327	8800-89FF	55296-55807	D800-D9FF	1800-19FF	Lower case characters
	35328-35839	8A00-8BFF	55808-56319	DA00-DBFF	1A00-1BFF	Upper case and graphics characters
	35840-36351	8C00-8DFF	56320-56831	DC00-DDFF	1C00-1DFF	Reversed lower case characters
	36352-36863	8E00-8FFF	56832-57343	DE00-DFFF	1E00-1FFF	Reversed upper case and graphics

# VIC 20 Screen & Border Colours

POKE 36879, X :									
Border									
Screen	BLK	WHT	RED	CYN	PUR	GRN	BLU	YEL	
BLK	8	9	10	11	12	13	14	15	
WHT	24	25	26	27	28	29	30	31	
RED	40	41	42	43	44	45	46	47	
CYN	56	57	58	59	60	61	62	63	
PUR	72	73	74	75	76	77	78	79	
GRN	88	89	90	91	92	93	94	95	
BLU	104	105	106	107	108	109	110	111	
YEL	120	121	122	123	124	125	126	127	
ORG	136	137	138	139	140	141	142	143	
Lt. ORG	152	153	154	155	156	157	158	159	
PNK	168	169	170	171	172	173	174	175	
Lt. CYN	184	185	186	187	188	189	190	191	
Lt. PUR	200	201	202	203	204	205	206	207	
Lt. GRN	216	217	218	219	220	221	222	223	
Lt. BLU	232	233	234	235	236	237	238	239	
Lt. YEL	248	249	250	251	252	253	254	255	

Mde:	IMM	ZPg	Z,X	(I,X)	(I),Y	ABS	A,X	A,Y
Byts:	2	2	2	2	2	3	3	3
ORA	09	05	15	01	11	0D	1D	19
AND	29	25	35	21	31	2D	3D	39
EOR	49	45	55	41	51	4D	5D	59
ADC	69	65	75	61	71	6D	7D	79
STA		85	95	81	91	8D	9D	99
LDA	A9	A5	B5	A1	B1	AD	BD	B9
CMP	C9	C5	D5	C1	D1	CD	DD	D9
SBC	E9	E5	F5	E1	F1	ED	FD	F9

Op Code ends in -1, -5, -9, or -D

Mde:	IMM	ZPg	Z,X	ABS	A,X
Byts:	2	2	2	3	3
BIT		24		2C	
STY		84	94	8C	
LDY	A0	A4	B4	AC	BC
CPY	C0	C4		CC	
CPX	E0	E4		EC	

Op Code ends in -0, -4, or -C

### Jim Butterfield

Mde:	IMM	ZPg	Z,X	Z,Y	ABS	A,X	A,Y
Byts:	2	2	2	2	3	3	3
ASL		06	16		0E	1E	
ROL		26	36		2E	3E	
LSR		46	56		4E	5E	
ROR		66	76		6E	7E	
STX		86		96	8E		
LDX	A2	A6		B6	AE		BE
DEC		C6	D6		CE	DE	
INC		E6	F6		EE	FE	

Op Code ends in -2, -6, or -E

Branches -0			Jumps		
Mde:	ABS	(IND)	Mde:	ABS	(IND)
BPL	10	BMI	30		
BVC	50	BVS	70		
BCC	90	BCS	B0		
BNE	D0	BEQ	F0		
		JMP	20	4C	6C

Single Byte Op Codes (* Accumulator Mode)																
	0-	1-	2-	3-	4-	5-	6-	7-	8-	9-	A-	B-	C-	D-	E-	F-
-0	BRK				RTI		RTS									
-8	PHP	CLC	PLP	SEC	PHA	CLI	PLA	SEI	DEY	TYA	TAY	CLV	INY	CLD	INX	SED
-A	ASL*		ROL*		LSR*		ROR*		TXA	TXS	TAX	TSX	DEX		NOP	

# Commodore 6845 Video Chip

POKE 59520, R#	POKE 59521, Value
R0	Horizontal total number of characters on line (Nht) including horizontal retrace. (true value = number + 1)
R1	Horizontal number of characters displayed (Nhd)
R2	Distance (in characters) from left to right margin of screen + 1
R3	Sync width. Lo nybble is vertical sync width (in lines) Hi nybble is horizontal sync (in characters).
R4	Number of display lines including retrace (Nvt)
R5	Vertical position of the edge of the screen.
R6	Number of display lines on screen (Nvd)
R7	Height of upper edge from bottom of screen (in lines displayed)
R8	Interlace and Skew: - Bit 0 1 = interlaced mode 0 = non interlaced mode Bit 1 if Bit 0 = 1 then interlace and video mode Bit 2 not used Bit 3 not used Bit 4 1 = scan from 32770 in memory Bit 5 1 = scan from 32772 in memory Bit 6 cursor (not implemented on the PET) Bit 7 cursor (not implemented on the PET)
R9	Number of lines between top of one display line and top of the next
R10	Cursor (not implemented on the PET)
R11	Cursor (not implemented on the PET)
R12	Control Register: Bit 0 add 256 to start address (512 for 8032) Bit 1 add 512 to start address (1024 for 8032) Bit 2 invert flyback Bit 3 invert video signal Bit 4 use top half of 4K character generator Bit 5 (not implemented on the PET) Bit 6 (not implemented on the PET) Bit 7 not used
R13	Value + 32768 is address of first character (multiply by 2 for 8032)
R14	Cursor location HI (not implemented on the PET)
R15	Cursor location LO (not implemented on the PET)
R16	Light pen position HI (read only)
R17	Light pen position LO (read only)

## Hexadecimal Conversion Chart

Hex	-0	-1	-2	-3	-4	-5	-6	-7	-8	-9	-A	-B	-C	-D	-E	-F	-00	-000
0-	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	0	0
1-	16	17	18	19	20	21	22	23	24	25	26	27	28	29	30	31	256	4096
2-	32	33	34	35	36	37	38	39	40	41	42	43	44	45	46	47	512	8192
3-	48	49	50	51	52	53	54	55	56	57	58	59	60	61	62	63	768	12288
4-	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	1024	16384
5-	80	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	1280	20480
6-	96	97	98	99	100	101	102	103	104	105	106	107	108	109	110	111	1536	24576
7-	112	113	114	115	116	117	118	119	120	121	122	123	124	125	126	127	1792	28672
8-	128	129	130	131	132	133	134	135	136	137	138	139	140	141	142	143	2048	32768
9-	144	145	146	147	148	149	150	151	152	153	154	155	156	157	158	159	2304	36864
A-	160	161	162	163	164	165	166	167	168	169	170	171	172	173	174	175	2560	40960
B-	176	177	178	179	180	181	182	183	184	185	186	187	188	189	190	191	2816	45056
C-	192	193	194	195	196	197	198	199	200	201	202	203	204	205	206	207	3072	49152
D-	208	209	210	211	212	213	214	215	216	217	218	219	220	221	222	223	3328	53248
E-	224	225	226	227	228	229	230	231	232	233	234	235	236	237	238	239	3584	57344
F-	240	241	242	243	244	245	246	247	248	249	250	251	252	253	254	255	3840	61440

## Bit Values

Bit	Dec	Hex
0	1	\$0001
1	2	0002
2	4	0004
3	8	0008
4	16	0010
5	32	0020
6	64	0040
7	128	0080
8	256	0100
9	512	0200
10	1024	0400
11	2048	0800
12	4096	1000
13	8192	2000
14	16384	4000
15	32768	8000